PD 1.038A

Series PVT312

International **IGR** Rectifier HEXFET® Power MOSFET Photovoltaic Relay

voltaic Relay Microelectronic Power IC Relay Single Pole, Normally Open, 0-250V, 190mA AC/DC

General Description

The PVT312 Photovoltaic Relay is a single-pole, normally open solid-state relay that can replace electromechanical relays in many applications. It utilizes International Rectifier's proprietary HEXFET power MOSFET as the output switch, driven by an integrated circuit photovoltaic generator of novel construction. The output switch is controlled by radiation from a GaAIAs light emitting diode (LED) which is optically isolated from the photovoltaic generator.

This SSR is specifically designed for telecom applications. PVT312L employs an active currentlimiting circuitry enabling it to withstand current surge transients.

PVT312 Relays are packaged in a 6-pin, molded DIP package with either through-hole or surface mount ("gull-wing") terminals. It is available in standard plastic shipping tubes or on tape-and-reel. Please refer to the Part Identification information opposite.

PVT312L Features

- HEXFET Power MOSFET output
 - Bounce-free operation
 - 4,000 V_{RMS} I/O isolation
 - Load current limiting
 - Linear AC/DC operation
 - Solid-State reliability
 - UL recognized ■



Applications

- On/Off Hook switch
- Dial-Out relay
- Ring injection relay
- Ground start
- General switching

Part Identification

PVT312L	current limit, through-hole
PVT312LS	current limit, surface-mount
PVT312LS-T	surface-mount, tape and reel
PVT312	no current limit, through-hole
PVT312S	no current limit, surface-mount
PVT312S-T	no current limit,
	surface-mount, tape and reel

(HEXFET is the registered trademark for International Rectifier Power MOSFETs)

Series PVT312 — HEXFET® Photovoltaic Relay

Electrical Specifications (-40°C \leq T_A \leq +85°C unless otherwise specified)

INPUT CHARACTERISTICS	Part Numbers	Units
	PVT312L PVT312	
Minimum Control Current (see figures 1 and 2)	2.0	mA
Maximum Control Current for Off-State Resistance @ T _A =+25°C	0.4	mA
Control Current Range (Caution: current limit input LED, see figure 6)	2.0 to 25	mA
Maximum Reverse Voltage	7.0	V

OUTPUT CHARACTERISTICS		312L	PVT312	
Operating Voltage Range	0 to ±250		±250	V(DC or AC peak)
Maximum Load Current @ T _A =+40°C, 5mA Control (see figures 1 and 2)	m Load Current @ T _A =+40°C, 5mA Control (see figures 1 and 2)			
A Connection	170		190	mA (AC or DC)
B Connection	190		210	mA (DC)
C Connection	300		320	mA (DC)
Maximum On-State Resistance @T _A =+25°C for 50mA pulsed load	ximum On-State Resistance @T _A =+25°C for 50mA pulsed load			
5mA Control (see figure4)	5mA Control (see figure4)			
A Connection	1	5	10	Ω
B Connection	8		5.5	Ω
C Connection	4.2	25	3	Ω
Maximum Off-State Leakage @T _A =+25°C, ±250V (see figure 5)	1.0		μA	
Current Limit @T _A =+25°C, 5mA Control				
Connection:	Α	С		
Minimum	190	330	n/a	mA
Maximum	300	560	n/a	mA
Maximum Turn-On Time @T _A =+25°C (see figure 7)	3.0		.0	ms
for 50mA, 100 V _{DC} load, 5mA Control				
Maximum Turn-Off Time @T _A =+25°C (See Fig. 6)	0.5		ms	
For 50mA, 100 V _{DC} load, 5mA Control				
Maximum Output Capacitance @ 50V _{DC}	50		pF	

GENERAL CHARACTERISTIC	ALL MODELS		
Minimum Dielectric Strength, Input-Out	4000	V _{RMS}	
Minimum Insulation Resistance, Input-Output @T _A =+25°C, 50%RH, 100V _{DC}		1012	Ω
Maximum Capacitance, Input-Output		1.0	pF
Maximum Pin Soldering Temperature (10 seconds maximum)		+260	°C
Ambient Temperature Range:	Operating	-40 to +85	°C
	Storage	-40 to +100	

Connection Diagrams













Figure 1. Typical Current Derating Curves



Figure 3. Linearity Characteristics



Figure 5. Typical Normalized Off-State Leakage



Figure 2. Typical Current Derating Curves



Figure 4. Typical Normalized On-Resistance



Figure 6. Input Characteristics (Current Controlled)

Series PVT312 — HEXFET® Photovoltaic Relay



International **ICR** Rectifier

 WORLD HEADQUARTERS:
 233 Kansas St., El Segundo, California 90245, Tel: (310) 322 3331

 EUROPEAN HEADQUARTERS:
 Hurst Green, Oxted, Surrey RH8 9BB, UK Tel: ++ 44 1883 713215

 IR CANADA:
 7321 Victoria Park Ave., Suite 201, Markham, Ontario L3R 2Z8, Tel: (905) 475 1897

 IR GERMANY:
 Saalburgstrasse 157, 61350 Bad Homburg Tel: ++ 49 6172 96590

 IR ITALY:
 Via Liguria 49, 10071 Borgaro, Torino Tel: ++ 39 11 451 0111

 IR FAR EAST:
 K&H Bldg., 2F, 3-30-4 Nishi-Ikeburo 3-Chome, Toshima-Ku, Tokyo, Japan 171 Tel: ++ 81 3 3983 0641

 IR SOUTHEAST ASIA:
 315 Outram Road, #10-02 Tan Boon Liat Building, Singapore 0316 Tel: ++ 65 221 8371

 http://www/irf.com/
 Data and specifications subject to change without notice.